


Output Ratings				
Voltage, Frequency		Prime	Standby	
400/230V, 50 Hz	kVA	160	175	
100, 2001, 50112	kW	128	140	
480/277V, 60 Hz	kVA			
400/2//۷,00112	kW			



Please refer to the output ratings technical data section for specific generator set outputs per voltage.



	3

Dimensions and Weights			
Length	mm	2450 (96.5)	
Width	mm	1010 (39.8)	
Height	mm	1554 (61.2)	
Weight (Dry)	kg	1590 (3505)	
Weight (Wet)	kg	1611 (3552)	

Ratings in accordance with ISO 8528, ISO 3046, IEC 60034, BS5000 and NEMA MG-1.22.

Generator set pictured may include optional accessories.

Prime Rating

These ratings are applicable for supplying continuous electrical power (at variable load) in lieu of commercially purchased power. There is no limitation to the annual hours of operation and this model can supply 10% overload power for 1 hour in 12 hours.

Standby Rating

These ratings are applicable for supplying continuous electrical power (at variable load) in the event of a utility power failure. No overload is permitted on these ratings. The alternator on this model is peak continuous rated (as defined in ISO 8528-3).

Standard Reference Conditions

Note: Standard reference conditions 25°C (77°F) Air Inlet Temp, 100m (328 ft) A.S.L. 30% relative humidity. Fuel consumption data at full load with diesel fuel with specific gravity of 0.85 and conforming to BS2869: 1998, Class A2.

FG Wilson offer a range of optional features to allow you to tailor our generator sets to meet your power needs. Options available include:

- Upgrade to CE Certification
- A wide range of Sound Attenuated Enclosures
- A variety of generator set control and synchronising panels
- · Additional alarms and shutdowns
- A selection of exhaust silencer noise levels

For further information on all of the standard and optional features accompanying this product please contact your local Dealer or visit:

www.fgwilson.com



Ratings and Per	Tormance Data		
Engine Make		Perkins	
Engine Model:		1106D-E70TAG3	
Alternator Make		Marelli	
Alternator Model:		MJB 250 MA4	
Control Panel:		0	
Base Frame:		Heavy Duty Fabricated	Steel
Circuit Breaker Type:		3 Pole MCCB	
Frequency:		50 HZ	60 HZ
Engine Speed: RPM	rpm	1500	
Fuel Tank Capacity:	litres (US gal)	327 (86.38)	
Fuel Consumption Prin	me litres (US gal)	36.9 (9.7)	
Fuel Consumption Sta	andby litres (US gal)	39.7 (10.5)	
Engine Technica	al Data		
No. of Cylinders		6	
Alignment		IN LINE	
Cycle		4 STROKE	
Bore	mm (in)	105 (4.1)	
Stroke	mm (in)	135 (5.3)	
Induction			O AIR CHARGE COOLED
Cooling Method		WATER	
Governing Type		ELECTRONIC	
Governing Class		ISO 8528 G2	
Compression Ratio		16.8:1	
Displacement	L (cu. in)	7 (427.8)	
Moment of Inertia:	kg m² (lb/in²)	1.53 (5228)	
Voltage		12	
Ground		Negative	
Battery Charger Amps		65	
Engine Weight Dry	kg (lb)	788 (1737)	
Engine Weight Wet	kg (lb)	822 (1812)	
Engine Perform	nance Data	50 Hz	60 Hz
		1500	00112
Engine Speed	rpm	148.1 (199)	
Gross Engine Power Pr		162.8 (218)	
Gross Engine Power St			
BMEP Prime BMEP Standby	kPa (psi) kPa (psi)	1689 (245) 1857 (269.3)	



Fuel System					
Fuel Filter Type:			Replaceable Eler	ment	
Recommended Fuel:			Class A2 Diesel		
Fuel Consumption at		110 % Load	100 % Load	75 % Load	50 % Load
50 Hz Prime:	I/hr (US gal/hr)	39.7 (10.5)	36.9 (9.7)	29.2 (7.7)	20.7 (5.5)
50 Hz Standby	l/hr (US gal/hr)	-	39.7 (10.5)	31.4 (8.3)	22.4 (5.9)
60 Hz Prime	I/hr (US gal/hr)				
60 Hz Standby	I/hr (US gal/hr)	-			

(Based on diesel fuel with a specific gravity of 0.83 and conforming to BS2869 classA2,EN590 $\,$

Air System		JU 112	Hz 60 Hz		
Air Filter Type:		Replaceable Element			
Combustion Air Flow Prime m ³ /	min (cfm)	11.9 (420)			
Combustion Air Flow Standby m ³ /	min (cfm)	12.4 (438)			
Max. Combustion Air Intake Restriction kPa		8 (32.1)			

Cooling System		50 Hz		60 Hz
Cooling System Capacity	l (US gal)	21 (5.5)		
Water Pump Type:			Centrifuga	ıl
Heat Rejected to Water & Lube Oil: Prime	kW (Btu/min)	64 (3640)		
Heat Rejected to Water & Lube Oil: Standby	kW (Btu/min)	72.5 (4123)		
Heat Radiation to Room*: Prime	kW (Btu/min)	35 (1990)		
Heat Radiation to Room*: Standby	kW (Btu/min)	37.3 (2121)		
Radiator Fan Load:	kW (hp)	4.5 (6)		
Radiator Cooling Airflow:	m³/min (cfm)	276 (9747)		
External Restriction to Cooling Airflow:	Pa (in H2O)	125 (0.5)		

^{*:} Heat radiated from engine and alternator

Designed to operate in ambient conditions up to 50°C (122°F).

Contact your local FG Wilson Dealer for power ratings at specific site conditions.

Lubrication Sys	tem	
Oil Filter Type:		Spin-On, Full Flow
Total Oil Capacity:	l (US gal)	17.5 (4.6)
Oil Pan Capacity:	l (US gal)	15.5 (4.1)
Oil Type:		API CH4 / CI4 15W-40

Oil Type:

Oil Cooling Method:

WATER

Exhaust System		50 Hz	60 Hz
Maximum Allowable Back Pressure:	kPa (in Hg)	15 (4.4)	
Exhaust Gas Flow: Prime	m³/min (cfm)	26.4 (932)	
Exhaust Gas Flow: Standby	m³/min (cfm)	26.6 (939)	
Exhaust Gas Temperature: Prime	°C (°F)	491 (916)	
Exhaust Gas Temperature: Standby	°C (°F)	491 (916)	



Alternator Physical Data						
No. of Bearings:				1		
Insulation Class:			Н			
Winding Pitch:				2/3		
Winding Code				M0		
Wires:				12		
Ingress Protection Rating:				IP23		
Excitation System:		SHUNT				
AVR Model:		Mark V				
dependant on voltage code selected						
Alternator Operating Da	ta					
Overspeed: rpm				2250		
Voltage Regulation: (Steady state) %			+/- 0.5			
Wave Form NEMA = TIF:			50			
Wave Form IEC = THF:	%	2				
Total Harmonic content LL/LN:	%	2				
Radio Interference:		EN 55011				
Radiant Heat: 50 Hz	kW (Btu/min)			10.7 (608)		
Radiant Heat: 60 Hz	kW (Btu/min)					
Alternator Performance	Data 50 Hz:					
		415/240 V	400/230 V	380/220 V		
Voltage Code						
Motor Starting Capability* kVA		224	208	188		
Short Circuit Capacity** %		300	300	300	300	
Reactances Xd		2.938	3.161	3.501		
		0.258	0.277	0.307		
X'd		0.258	0.277	0.507		

Voltage Code

Motor Starting Capability*	kVA					
Short Circuit Capacity**	%	300	300	300	300	300
Reactances	Xd					
	X'd					
	X"d					

Reactances shown are applicable to prime ratings.

^{*}Based on 30% voltage dip at 0.6 power factor.

^{**} With optional independant excitation system (PMG / AUX winding)



Output Ratings	50 Hz				
		Prime		Standby	
Voltage Code	kVA	kW	kVA	kW	
415/240V	160	128	175	140	
400/230V	160	128	175	140	
380/220V	160	128	175	140	
230/115V					
220/127V					
220/110V					
200/115V					
240V					
230V					
220V					
Output Ratings	60 Uz				
Output Ratings	00112	Prime		Standby	
Voltage Code	kVA	kW	kVA	kW	
480/277V					
440/254V					
416/240V					
400/230V					
380/220V					
240/139V					
240/120V					
230/115V					
220/127V					
220/110V					
208/120V					
240/120					
220/110					





Dealer Contact Details



01953 454540 www.stuartgroup.ltd.uk enquiries@stuartgroup.info





Documentation

Operation and maintenance manual including circuit wiring diagrams.

Generator Set Standards

The equipment meets the following standards: BS5000, ISO 8528, ISO 3046, IEC 60034, NEMA MG-1.22.

Warranty

6.8 – 750 kVA electric power generation products in prime applications the warranty period is 12 months from date of start-up, unlimited hours (8760). For standby applications the warranty period is 24 months from date of start-up, limited to 500 hours per year.

730 – 2500 kVA electric power generation products in prime applications the warranty period is 12 months from date of start-up, unlimited hours (8760 hours) or 24 months from date of start-up, limited to 6000 hours. For standby applications the warranty period is 36 months from date of start-up, limited to 500 hours per year.

FG Wilson manufactures product in the following locations:

Northern Ireland • Brazil • China • India

With headquarters in Northern Ireland, FG Wilson operates through a Global Dealer Network. To contact your local Sales Office please visit the FG Wilson website at www.fgwilson.com.

FG Wilson is a trading name of Caterpillar (NI) Limited.